


**the
t.amp**

Proline 3000
power amplifier



Musikhaus Thomann
Thomann GmbH
Hans-Thomann-Straße 1
96138 Burgebrach
Germany
Telephone: +49 (0) 9546 9223-0
E-mail: info@thomann.de
Internet: www.thomann.de

06.06.2018, ID: 168990 (V2)

Table of contents

1	General information	4
	1.1 Further information.....	5
	1.2 Notational conventions.....	6
	1.3 Symbols and signal words.....	6
2	Safety instructions	8
3	Installation and starting up	13
4	Connections and controls	17
5	Technical specifications	22
6	Plug and connection assignment	24
7	Cleaning	27
8	Protecting the environment	28

1 General information

This manual contains important instructions for the safe operation of the unit. Read and follow the safety instructions and all other instructions. Keep the manual for future reference. Make sure that it is available to all those using the device. If you sell the unit please make sure that the buyer also receives this manual.

Our products are subject to a process of continuous development. Thus, they are subject to change.

1.1 Further information

On our website (www.thomann.de) you will find lots of further information and details on the following points:

Download	This manual is also available as PDF file for you to download.
Keyword search	Use the search function in the electronic version to find the topics of interest for you quickly.
Online guides	Our online guides provide detailed information on technical basics and terms.
Personal consultation	For personal consultation please contact our technical hotline.
Service	If you have any problems with the device the customer service will gladly assist you.

1.2 Notational conventions

This manual uses the following notational conventions:

Letterings

The letterings for connectors and controls are marked by square brackets and italics.

Examples: *[VOLUME]* control, *[Mono]* button.

1.3 Symbols and signal words

In this section you will find an overview of the meaning of symbols and signal words that are used in this manual.

Signal word	Meaning
DANGER!	This combination of symbol and signal word indicates an immediate dangerous situation that will result in death or serious injury if it is not avoided.
CAUTION!	This combination of symbol and signal word indicates a possible dangerous situation that can result in minor injury if it is not avoided.
NOTICE!	This combination of symbol and signal word indicates a possible dangerous situation that can result in material and environmental damage if it is not avoided.
Warning signs	Type of danger
	Warning – high-voltage.
	Warning – danger zone.

2 Safety instructions

Intended use

This device amplifies electric audio frequency signals to operate passive speakers. Use the device only as described in this user manual. Any other use or use under other operating conditions is considered to be improper and may result in personal injury or property damage. No liability will be assumed for damages resulting from improper use.

This device may be used only by persons with sufficient physical, sensorial, and intellectual abilities and having corresponding knowledge and experience. Other persons may use this device only if they are supervised or instructed by a person who is responsible for their safety.

Safety



DANGER!

Danger for children

Ensure that plastic bags, packaging, etc. are disposed of properly and are not within reach of babies and young children. Choking hazard!

Ensure that children do not detach any small parts (e.g. knobs or the like) from the unit. They could swallow the pieces and choke!

Never let children unattended use electrical devices.



DANGER!

Electric shock caused by high voltages inside

Within the device there are areas where high voltages may be present. Never remove any covers.

There are no user-serviceable parts inside.

Do not use the device if covers, protectors or optical components are missing or damaged.



DANGER!

Electric shock caused by short-circuit

Always use proper ready-made insulated mains cabling (power cord) with a protective contact plug. Do not modify the mains cable or the plug. Failure to do so could result in electric shock/death or fire. If in doubt, seek advice from a registered electrician.



CAUTION!

Possible hearing damage

With loudspeakers or headphones connected, the device can produce volume levels that may cause temporary or permanent hearing impairment.

Do not operate the device permanently at a high volume level. Decrease the volume level immediately if you experience ringing in your ears or hearing impairment.



CAUTION!

Risk of injury due to heavy weight

Due to the heavy weight of the device, at least two persons are required for transport and installation.



NOTICE!

Risk of fire

Do not block areas of ventilation. Do not install the device near any direct heat source. Keep the device away from naked flames.



NOTICE!

Operating conditions

This device has been designed for indoor use only. To prevent damage, never expose the device to any liquid or moisture. Avoid direct sunlight, heavy dirt, and strong vibrations.



NOTICE!

Power supply

Before connecting the device, ensure that the input voltage (AC outlet) matches the voltage rating of the device and that the AC outlet is protected by a residual current circuit breaker. Failure to do so could result in damage to the device and possibly injure the user.

Unplug the device before electrical storms occur and when it is unused for long periods of time to reduce the risk of electric shock or fire.



NOTICE!

Magnetic fields

The device generates strong magnetic fields that can interfere with the function of poorly shielded devices. The strongest magnetic fields are directly above and below the power amplifier. Therefore, never place sensitive devices such as pre-amplifiers, radio transmission systems, or tape decks directly above or below the power amplifier. When installing the power amplifier into a rack, you should place it in the lowest position, and further equipment such as pre-amplifiers in the highest position.

3 Installation and starting up

Unpack and carefully check that there is no transportation damage before using the unit. Keep the equipment packaging. To fully protect the device against vibration, dust and moisture during transportation or storage use the original packaging or your own packaging material suitable for transport or storage, respectively.

Create all connections while the device is off. Use the shortest possible high-quality cables for all connections. Take care when running the cables to prevent tripping hazards.



DANGER!

Electric shock caused by high voltages at the power amplifier output

The output voltages of modern high-performance amplifiers may result in death or serious injury.

Never touch the bare ends of loudspeaker cables when the amplifier is on.



CAUTION!

Risk of injury due to heavy weight

Due to the heavy weight of the device, at least two persons are required for transport and installation.



NOTICE!

Magnetic fields


The device generates strong magnetic fields that can interfere with the function of poorly shielded devices. The strongest magnetic fields are directly above and below the power amplifier. Therefore, never place sensitive devices such as pre-amplifiers, radio transmission systems, or tape decks directly above or below the power amplifier. When installing the power amplifier into a rack, you should place it in the lowest position, and further equipment such as pre-amplifiers in the highest position.

Rack mounting


The unit has been designed for rack mounting in a standard 19-inch rack; it occupies three rack units.

Possible operation modes

Depending on the individual application, the amplifier can be used in different operation modes:

Stereo mode

The two amplifier channels operate independently of one another, either channel (A and B) is amplified and connected to loudspeakers, the volume can be controlled separately for the two outputs.

Parallel mode

The two amplifier channels receive the same input signal from channel A and loudspeakers are connected to each amplifier. The volume is controlled via the control knob for channel A.

Bridged mode

Both power amp channels are internally wired for providing double the output power. Only the input signal from channel A is amplified and loudspeakers are connected only to the correspondingly marked output. The volume is controlled via the control knob for channel A.

On each output of the amplifier, the overall impedance resulting from the individual impedances of the connected speakers must not fall below the minimum allowable impedance of the amp's output. If you want to connect multiple speakers to one amplifier output, note the following:


- when connecting speakers in series, the impedances add up.
- when connecting speakers in parallel, the reciprocal value of the total impedance is equal to the sum of the reciprocal values of the individual impedances.

This means, for example with two speakers with the same impedance: In series connection, impedance is doubled. In parallel connection, it's halved.

Detailed information on this topic can be found in our online guide 'Speakers' (www.thomann.de).

4 Connections and controls

Front panel




Proline 3000

1	<i>[POWER]</i>	Power on/off switch. Turns the device on and off.
2	<i>[CHANNEL A]/ [CHANNEL B]</i>	Volume control for the respective channel
3	LED panel	
	<i>[CLIP]</i>	Lights under the following conditions: <ul style="list-style-type: none">■ Channel overdrive. In this case, reduce the volume until the LED turns off.■ Short-circuit at the output. Immediately turn off the device, fix the short-circuit and turn on the device again.
	<i>[SGL]</i>	Indicates the presence of an input signal.

<i>[PRO]</i>	Lights under the following conditions: <ul style="list-style-type: none">■ Three to five seconds after turning on or off when the device is in an unstable state.■ The temperature of the amplifier blocks has reached 85°C.■ One or more protection circuits have been triggered or the device is defective.
<i>[STR]</i>	Lights when the device is operated in stereo mode.
<i>[PAR]</i>	Lights when the device is operated in parallel mode.
<i>[BRI]</i>	Lights when the device is operated in bridged mode.

Rear panel



- | | |
|---|---|
| 4 | XLR mounting socket for the input signal in channel A |
| 5 | 1/4" phone socket for the input signal in channel A |
| 6 | XLR mounting socket for the input signal in channel B |
| 7 | 1/4" phone socket for the input signal in channel B |

8	Selector switch for operating mode <ul style="list-style-type: none">■ [PAR]: Parallel mode■ [STR]: Stereo mode■ [BR]: Bridged mode
9	Ground/Lift switch <p>If hum is caused by a ground loop, you can use this switch to disconnect the connection between the earth pin of the device and the signal ground of the device.</p>
10	Lockable chassis connector (Speaker Twist) for speaker output in bridged mode (1+, 2+: positive; 1-, 2-: negative)
11	Lockable chassis connector (Speaker Twist) for speaker output for channel A (1+, 2+: positive; 1-, 2-: negative)
12	Lockable chassis connector (Speaker Twist) for speaker output for channel B (1+, 2+: positive; 1-, 2-: negative)
13	[RESET] <p>Resettable fuse. The fuse switches off at too high current consumption of the amplifier. Once the problem is solved, the fuse will automatically be reset, the device is operational again. The switch can be used to force a reset.</p>
14	Power cable.
15	Fan

5 Technical specifications

Output power	Stereo, 8 Ω : 2 \times 1100 W
	Stereo, 4 Ω : 2 \times 1500 W
	Stereo, 2 Ω : 2 \times 1800 W
	Bridged, 8 Ω : 3000 W
	Bridged, 4 Ω : 3600 W
	Parallel, 8 Ω : 2 \times 1100 W
	Parallel, 4 Ω : 2 \times 1500 W
	Parallel, 2 Ω : 2 \times 1800 W
Frequency response, \pm 1,5 dB	20 Hz...20 kHz
Input sensitivity	0.77 V
Signal-to-noise ratio	\geq 100 dB
Slew rate	45 V/ μ s

Crosstalk at rated power @ 8 Ω, 1 kHz	> 70 dB
Damping factor	> 700
Inputs	XLR sockets, 1/4" phone sockets (balanced)
Outputs	Lockable chassis connector (Speaker Twist)
Cooling system	Temperature-controlled fan cooling
Operating supply voltage	220 – 240 V ~ 50/60 Hz
Power consumption (at 50 % of rated output power @ 8 Ω)	1550 W
Dimensions (W × H × D)	482 mm × 132 mm × 460.5 mm
Weight	37 kg

6 Plug and connection assignment

Introduction

This chapter will help you select the right cables and plugs to connect your valuable equipment in such a way that a perfect sound experience is ensured.

Please note these advices, because especially in 'Sound & Light' caution is indicated: Even if a plug fits into the socket, an incorrect connection may result in a destroyed power amp, a short circuit or 'just' in poor transmission quality!

Balanced and unbalanced transmission

Unbalanced transmission is mainly used in semi-professional environment and in hifi use. Instrument cables with two conductors (one core plus shielding) are typical representatives of the unbalanced transmission. One conductor is ground and shielding while the signal is transmitted through the core.

Unbalanced transmission is susceptible to electromagnetic interference, especially at low levels, such as microphone signals and when using long cables.

In a professional environment, therefore, the balanced transmission is preferred, because this enables an undisturbed transmission of signals over long distances. In addition to the conductors 'Ground' and 'Signal', in a balanced transmission a second core is added. This also transfers the signal, but phase-shifted by 180°.

Since the interference affects both cores equally, by subtracting the phase-shifted signals, the interfering signal is completely neutralized. The result is a pure signal without any noise interference.

1/4" TS phone plug (mono, unbalanced)




1	Signal
2	Ground, shielding

1/4" TRS phone plug (mono, balanced)



1	Signal (in phase, +)
2	Signal (out of phase, -)
3	Ground

XLR plug (balanced)



1	Ground, shielding
2	Signal (in phase, +)
3	Signal (out of phase, -)
4	Shielding on plug housing (option)

Speaker Twist chassis connector



1, +	Signal 1 (in phase)
1, -	Signal 1 (out of phase)
2, +	Signal 2 (in phase)
2, -	Signal 2 (out of phase)

7 Cleaning

Fan grids

The fan grids of the device must be cleaned on a regular basis to remove dust and dirt. Before cleaning, switch off the device and disconnect AC-powered devices from the mains. Use a lint-free damp cloth for cleaning. Never use solvents or alcohol for cleaning.

8 Protecting the environment

Disposal of the packaging material



For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling.

Ensure that plastic bags, packaging, etc. are properly disposed of.

Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.

Disposal of your old device



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE) in its currently valid version. Do not dispose with your normal household waste.

Dispose of this device through an approved waste disposal firm or through your local waste facility. When discarding the device, comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.

Proline 3000



