


Features

- Two fixed antennas for optimum reception quality
- Automatic frequency scan, four to six parallel frequencies
- Infrared interface for sending the frequency selection from the receiver to the transmitter (ACT-Sync)
- Outputs:
XLR, 1/4" phone socket
- Power supply: 12 V , a suitable plug-in power supply unit and mounting accessories for the installation in a rack are included in delivery

Technical specifications

- Output:
 - XLR chassis plug (balanced)
 - 1/4" phone socket (unbalanced)
- Output level adjustment:
–10 dB ... +20 dB
- Frequency range:
2.400 GHz ... 2.4835 GHz
- Sensitivity : –95 dBm
- Audio sample rate : 24 bit / 44.1 kHz
- NF frequency response:
20 Hz ... 20 kHz (–2 dB)
- Distortion (1 kHz): 0.1 %
- Signal-to-noise ratio:
> 115 dB (A)
- Operating voltage supply:
AC 12 – 15 V , 1000 mA
- Power consumption:
1.6 W
- Dimensions (B × H × T, without antennas):
210 mm × 44 mm × 180 mm
- Weight: 0.75 kg



Ensure that plastic bags, packaging, etc. are properly disposed of and are not in the reach of babies and young children. Choking hazard!



For the packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE). Do not dispose with your normal household waste. Dispose of this device through an approved waste disposal firm or through your local waste facility. When discarding the device, comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.

Please find a more detailed manual under www.thomann.de.