



Area Flood 30 IP,
Area Flood 50 IP,
Area Flood 80 IP,
Area Flood 100 IP


LED floodlight

Musikhaus Thomann
Thomann GmbH
Hans-Thomann-Straße 1
96138 Burgebrach
Germany
Telephone: +49 (0) 9546 9223-0
E-mail: info@thomann.de
Internet: www.thomann.de

10.02.2020, ID: 472585, 472586, 472587, 472588

Table of contents

1	General information	5
	1.1 Further information.....	6
	1.2 Symbols and signal words.....	7
2	Safety instructions	9
3	Features	13
4	Installation and starting up	15
5	Technical specifications	18
6	Cleaning	26
7	Protecting the environment	27



1 General information

This user manual contains important information on the safe operation of the device. Read and follow all safety notes and all instructions. Save this manual for future reference. Make sure that it is available to all persons using this device. If you sell the device to another user, be sure that they also receive this manual.

Our products and user manuals are subject to a process of continuous development. We therefore reserve the right to make changes without notice. Please refer to the latest version of the user manual which is ready for download under www.thomann.de.

1.1 Further information





On our website (www.thomann.de) you will find lots of further information and details on the following points:

Download	This manual is also available as PDF file for you to download.
Keyword search	Use the search function in the electronic version to find the topics of interest for you quickly.
Online guides	Our online guides provide detailed information on technical basics and terms.
Personal consultation	For personal consultation please contact our technical hotline.
Service	If you have any problems with the device the customer service will gladly assist you.

1.2 Symbols and signal words

In this section you will find an overview of the meaning of symbols and signal words that are used in this manual.

Signal word	Meaning
DANGER!	This combination of symbol and signal word indicates an immediate dangerous situation that will result in death or serious injury if it is not avoided.
WARNING!	This combination of symbol and signal word indicates a possible dangerous situation that can result in death or serious injury if it is not avoided.
NOTICE!	This combination of symbol and signal word indicates a possible dangerous situation that can result in material and environmental damage if it is not avoided.

Warning signs	Type of danger
	Warning – high-voltage.
	Warning – dangerous optical radiation.
	Warning – suspended load.
	Warning – danger zone.

2 Safety instructions

Intended use

This device is intended for use as an electronic lighting effect by means of LED technology. The device is designed for professional use and is not suitable for use in households. Use the device only as described in this user manual. Any other use or use under other operating conditions is considered to be improper and may result in personal injury or property damage. No liability will be assumed for damages resulting from improper use.

This device may be used only by persons with sufficient physical, sensorial, and intellectual abilities and having corresponding knowledge and experience. Other persons may use this device only if they are supervised or instructed by a person who is responsible for their safety.

Extend the life of the device by regular breaks in operation and avoid switching it on and off frequently. This device is not suitable for continuous use.

Safety



DANGER!

Danger for children

Ensure that plastic bags, packaging, etc. are disposed of properly and are not within reach of babies and young children. Choking hazard!

Ensure that children do not detach any small parts (e.g. knobs or the like) from the unit. They could swallow the pieces and choke!

Never let children unattended use electrical devices.



DANGER!

Electric shock caused by high voltages inside

Within the device there are areas where high voltages may be present. Never remove any covers.

There are no user-serviceable parts inside.

Do not use the device if covers, protectors or optical components are missing or damaged.



DANGER!

Electric shock caused by short-circuit

Do not modify the mains cable or the plug. Failure to do so could result in electric shock/death or fire. If in doubt, seek advice from a registered electrician.



WARNING!

Eye damage caused by high light intensity

Never look directly into the light source.



DANGER!

Possible danger caused by damaged front glass

Damaged front glass can result in injuries caused by falling glass fragments.

Furthermore moisture could penetrate into the device and cause short circuits or irreparable damages of the device. Risk of fire and loss of life.

Only use the device when the front glass is not damaged.



NOTICE!

Risk of fire

Do not block areas of ventilation. Do not install the device near any direct heat source. Keep the device away from naked flames.



NOTICE!

Voltage supply

Connect the device directly to the power grid. It must not be connected to a dimmer.

Before connecting the device, you have to ensure that the rated voltage indicated on the device matches the voltage of the power grid available in the operating place. You must also take care that the power grid is protected by a residual current circuit breaker. Failure to do so can result in damage to the device and injury to the user.

In case a thunderstorm is coming up or you're not going to use the device for a longer period of time, disconnect it from the power grid to reduce the risk of electric shock and fire.

3 Features

The LED floodlight is particularly suitable for professional lighting tasks. The high-quality reflector ensures even illumination and maximum light output.

The device is characterized by:

- Flat, powder-coated housing
- Swivelling and lockable bracket (180 °)
- Large and even illumination
- High luminous power with low power consumption
- Outdoor use due to protection class IP65

For technological reasons, the light output of LEDs decreases over their lifetime. This effect increases with higher operating temperature. You can extend the service life of the illuminants by providing adequate ventilation and operating the LEDs with the lowest possible brightness.

Information about protection class IP65

Equipment with protection class IP65 are dust-tight and completely protected against contact (first code number). They are also protected against splash water from any angle (second code digit). That is why this equipment can also be used outdoors. Event technology equipment is generally only designed for temporary use however (event lighting) and not for permanent use outdoors.

The specified protection class does not make a statement about the weather resistance of the equipment (resistance to changing ambient conditions as well as against the effects of sunlight and UV rays).

The seals and screw connections of the equipment must be checked regularly to ensure a fault-free operation. In cases of doubt, consult a specialist workshop in due time.

4 Installation and starting up

Unpack and check carefully there is no transportation damage before using the unit. Keep the equipment packaging. To fully protect the product against vibration, dust and moisture during transportation or storage use the original packaging or your own packaging material suitable for transport or storage, respectively.



WARNING!

Risk of injury caused by falling objects

Make sure that the installation complies with the standards and rules that apply in your country. Always secure the device with a secondary safety attachment, such as a safety cable or a safety chain.



NOTICE!

Risk of overheating

Always ensure sufficient ventilation.

The ambient temperature must not exceed the limits stated in the chapter Technical Specifications of the User Manual.



NOTICE!

Use of stands

When mounting the device onto a stand, ensure that the stand is in a safe and stable position and that the weight of the device does not exceed the maximum permissible load capacity of the stand.

Mounting options

You can install the unit in hanging or standing position. When in use, the device must always be attached to a solid surface or an approved truss. Use the openings of the bracket provided for mounting.

Always work from a stable platform whenever installing, moving or servicing the unit. In doing so, the area underneath the unit must be cordoned off.

The safety cable must be attached to the bracket.



Please note that this device must not be connected to a dimmer.

Create all connections while the device is off. Use the shortest possible high-quality cables for all connections. Take care when running the cables to prevent tripping hazards.

5 Technical specifications

Varytec Area Flood 30 IP (item no. 472585)

Light source	72 × OSRAM 2835 SMD LEDs, cold white, 0.5 W each	
Light source properties	Colour temperature	6000 K
	Colour rendering index	CRI > 80
	Light output	approx. 110 lm / watt
	Lifetime LED chip	approx. 20.000 hours
Optical properties	Beam angle	120 °, symmetrical
Input connections	Voltage supply	Power cable with safety plug (120 cm)
Power consumption	30 W	
Operating supply voltage	100 – 240 V ~ 50/60 Hz	
Protection class	IP65	
Mounting options	hanging, standing	

Dimensions (W × H × D), bracket horizontal	192 mm × 172 mm × 92 mm	
Weight	1.8 kg	
Ambient conditions	Temperature range	-30 °C...50 °C
	Relative humidity	50 %, non-condensing

Varytec Area Flood 50 IP (item no. 472586)

Light source	120 × OSRAM 2835 SMD LEDs, cold white, 0.5 W each	
Light source properties	Colour temperature	6000 K
	Colour rendering index	CRI > 80
	Light output	approx. 110 lm / watt
	Lifetime LED chip	approx. 20.000 hours
Optical properties	Beam angle	120 °, symmetrical
Input connections	Voltage supply	Power cable with safety plug (120 cm)
Power consumption	50 W	
Operating supply voltage	100 – 240 V ~ 50/60 Hz	
Protection class	IP65	
Mounting options	hanging, standing	
Dimensions (W × H × D), bracket horizontal	235 mm × 200 mm × 117 mm	
Weight	2.4 kg	

Ambient conditions	Temperature range	-30 °C...50 °C
	Relative humidity	50 %, non-condensing

Varytec Area Flood 80 IP (item no. 472587)

Light source	192 × OSRAM 2835 SMD LEDs, cold white, 0.5 W each	
Light source properties	Colour temperature	6000 K
	Colour rendering index	CRI > 80
	Light output	approx. 110 lm / watt
	Lifetime LED chip	approx. 20.000 hours
Optical properties	Beam angle	120 °, symmetrical
Input connections	Voltage supply	Power cable with safety plug (120 cm)
Power consumption	80 W	
Operating supply voltage	100 – 240 V ~ 50/60 Hz	
Protection class	IP65	
Mounting options	hanging, standing	
Dimensions (W × H × D), bracket horizontal	285 mm × 250 mm × 117 mm	
Weight	3.6 kg	

Ambient conditions	Temperature range	-30 °C...50 °C
	Relative humidity	50 %, non-condensing

Varytec Area Flood 100 IP (item no. 472588)

Light source	240 × OSRAM 2835 SMD LEDs, cold white, 0.5 W each	
Light source properties	Colour temperature	6000 K
	Colour rendering index	CRI > 80
	Light output	approx. 110 lm / watt
	Lifetime LED chip	approx. 20.000 hours
Optical properties	Beam angle	120 °, symmetrical
Input connections	Voltage supply	Power cable with safety plug (120 cm)
Power consumption	100 W	
Operating supply voltage	100 – 240 V ~ 50/60 Hz	
Protection class	IP65	
Mounting options	hanging, standing	
Dimensions (W × H × D), bracket horizontal	360 mm × 290 mm × 190 mm	

Weight	4.8 kg	
Ambient conditions	Temperature range	-30 °C...50 °C
	Relative humidity	50 %, non-condensing

Further information

Outdoor-ready	Yes
Colour mixture	CW
Floor housing	No
Fanless	Yes
Remote control	Not possible
Wireless DMX	No
Housing colour	black

6 Cleaning

Optical lenses

Clean the optical lenses, that are accessible from the outside, regularly in order to optimize the light output. The frequency of cleaning depends on the operating environment: wet, smoky or particularly dirty surroundings can cause more accumulation of dirt on the optics of the device.

- Clean with a soft cloth using our lamp and lens cleaner (item no. 280122).
- Always dry the parts carefully.

7 Protecting the environment

Disposal of the packaging material



For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling.

Ensure that plastic bags, packaging, etc. are properly disposed of.

Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.

Disposal of your old device



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE) in its currently valid version. Do not dispose with your normal household waste.

Dispose of this device through an approved waste disposal firm or through your local waste facility. When discarding the device, comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.

