

ASA 3000

RF Wireless Systems | 3000 Series Receivers

Cat. No. 009423

General Description

The ASA 3000 is an active antenna splitter for multi-channel wireless microphone systems with up to 16 channels (8 x EM 3031, 8 x EM 3032 or 8 x EM 3532). The ASA 3000 is suitable for the entire UHF range but can optionally be equipped with selective input filter modules to narrow the input frequency range.



Technical Data

RF frequency range	470–870 MHz
Transmission loss.....	0 dB
Nominal impedance	50 Ω
RF input	BNC
Booster Feed	12 V, 70 mA
Mains voltage.....	100 - 240 V
Mains frequency	50 - 60 Hz
Dimensions	19", 1U

General Features

- Active splitter
- Broadband input modules
- Optional selective input modules
- DC power supplied to antenna head amplifiers
- Robust 19" housing in 3000 Series design

Accessories

- Input module IM 3000

Cat. No. 005241

Product Variants

- ASA 3000-EU, EU cable
- ASA 3000-UK, UK cable
- ASA 3000-US, US cable

Cat. No. 009423

Cat. No. 009408

Cat. No. 009407