



Features

- Eightfold Power Twist Splitter
- 20 A resettable fuse
- 1 × Power Twist input
- 1 × Power Twist through-connection
- 8 × Power Twist outputs
- 2 × M10 mounting thread
- 1 × M10 eye bolt, supplied

Technical specifications

▪ Input connections	Power In	1 × lockable input socket (Power Twist)
▪ Output connections	Power Thru Power Out	1 × lockable output socket (Power Twist) 8 × lockable output socket (Power Twist)
▪ Degree of protection		IP20
▪ Diameter inner wiring		2.5 mm ²
▪ Supply voltage		230 V ~ 50 Hz
▪ Load capacity		20 A
▪ Dimensions (W × H × D)		430 mm × 60 mm × 60 mm
▪ Weight		1.6 kg
▪ Colour		black
▪ Material		metal
▪ Ambient conditions	Temperature range	0 °C...40 °C
	Relative humidity	20 %...80 % (non-condensing)

Intended use

This device is used to distribute electrical power to several connected consumers. Any other use or use under other operating conditions is considered to be improper and may result in personal injury or property damage. No liability will be assumed for damages resulting from improper use.

Danger for children

Ensure that plastic bags, packaging, etc. are disposed of properly and are not within reach of babies and young children. Choking hazard! Ensure that children do not detach any small parts from the unit. They could swallow the pieces and choke! Never let children unattended use electrical devices.

Electric shock caused by high voltages inside

Within the device there are areas where high voltages may be present. Never remove any covers. There are no user-serviceable parts inside. Do not use the device if covers, protectors or optical components are missing or damaged..

Electric shock caused by short-circuit

Do not modify the mains cable or the plug. Failure to do so could result in electric shock/death or fire. If in doubt, seek advice from a registered electrician.



Risk of fire

Do not block areas of ventilation. Do not install the device near any direct heat source. Keep the device away from naked flames.

Power supply

Before connecting the device, ensure that the input voltage (AC outlet) matches the voltage rating of the device and that the AC outlet is protected by a residual current circuit breaker. Failure to do so could result in damage to the device and possibly injure the user. Unplug the device before electrical storms occur and when it is unused for long periods of time to reduce the risk of electric shock or fire.



For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE) in its currently valid version. Do not dispose with your normal household waste. Dispose of this device through an approved waste disposal firm or through your local waste facility. When discarding the device, comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.