



Features

- Condenser microphone with cardioid polar pattern
- Operation with exchangeable lithium-ion battery
- Charging contacts for charger system GigA Pro BC2
- Three-digit display for battery capacity
- Infrared interface for ACT-Sync

Technical specifications

- Frequency range :
2.400 GHz ... 2.4835 GHz
- Maximum transmission power: 10 mW
- Maximum output level: 6,5 dBV
- Input impedance: 1,0 MΩ
- Operating voltage supply:
1 Lithium-ion battery ICR-18500
- Operating time:
> 10 h (after four hours of charging time),
> 1 h (after 25 minutes of charging time)
- Dimensions (L × D):
248 mm × 50 mm
- Weight: 255 g



Ensure that plastic bags, packaging, etc. are properly disposed of and are not in the reach of babies and young children. Choking hazard!



For the packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE). Do not dispose with your normal household waste.

Dispose of this device through an approved waste disposal firm or through your local waste facility. When discarding the device, comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.



Batteries do contain some hazardous chemicals so they should not be thrown away with the normal household waste. Please use local collection sites. Before disposing of the device remove the lithium batteries. Protect used lithium batteries against potential short circuits, e.g. by covering the poles with adhesive tape.

Please find a more detailed manual under www.thomann.de.