EXPEDITION XP1000

Portable PA with Bluetooth®





Samson's Expedition XP1000 Portable PA with *Bluetooth* is an all-in-one sound system that goes anywhere you want great sound, weighing just over 50 pounds. The Expedition XP1000 is *Bluetooth*-enabled, so you can pair it with your smartphone, laptop or tablet and play your music without any need for cables. It's perfect for musical performances, parties, presentations, classrooms and the rest of a rapidly pairing world.

A removable 10-channel mixer with 16 presets of 24-bit digital effects powers the XP1000 with an 1000-watt (2 x 500) lightweight, Class D amplifier. The mixer features four Mic/Line channels, each with XLR and 1/4-inch inputs for connecting microphones or line level/active instruments. It also includes three stereo input channels for connecting external devices like MP3 players, keyboards and more. Each channel features bass and treble controls. The XP1000 also includes a USB input for use with the Samson USB Digital Wireless System accessory (not included). In addition, the mixer has a phantom power switch to enable the integration of condenser microphones into your PA setup.

The XP1000's 2-way vented speakers give you a clean, powerful stereo sound. They produce deep bass tones, as well as wide dispersion and loud, crystal clear audio, through 10-inch low frequency drivers and custom 1-inch tweeters with $60^{\circ} \times 90^{\circ}$ coverage. For display flexibility, these ABS, high impact plastic enclosures feature integrated 1 3/8-inch speaker stand mounts, as well as a 30° kickback design for use as floor monitors.

The Expedition XP1000 stands out as a complete portable PA system that is perfect for medium- to large-sized musical, educational, business and recreational applications

FEATURES

- Packs up into a single portable unit that weighs just over 50 pounds
- Bluetooth connectivity to connect wireless
 music sources
- Dual 2-way speaker enclosures with 10-inch woofers
- 1-inch high frequency drivers
- Lightweight, Class D amplifier produces 1000 watts (2 x 500) of stereo power
- Removable 10-channel mixer with 16 presets of 24-bit digital effects
- Bass and treble controls on each channel
- Four Mic/Line inputs (XLR and 1/4-inch jacks) for microphone, guitars and other line level devices
- 1/4-inch, RCA, combo1/4-inch/RCA stereo inputs for connecting external devices (MP3 players, keyboards, etc.)

- USB input for use with Samson USB Digital Wireless System accessory (not included)
- Phantom power for condenser microphones
- Two 1/4-inch Monitor outputs allow connections to external powered monitors
- LR RCA outputs for external recorders
- Music/Speech switch for optimizing output EQ for speech or music playback
- 6-segment level meter with limiter indicator
- Integrated 1 3/8-inch speaker stand mount
- 30° kickback design for using enclosures as floor monitors
- · Speaker cables included



 $\odot 2013$ Samson. Preliminary Literature. All product descriptions and specs subject to change.