



### Caution!

- ▶ Never remove the screen holding the capsule, as this may damage the microphone!
- ▶ Never drop the mic, as this may cause severe damage!
- ▶ When the microphone is not in use, take it out of its clamp and put it in its case. Clean with damp cloth only.

Connection / Supply	Mini USB & XLR / USB 5 V
Transducer concept	Dynamic
Directivity	Cardioid
Frequency response	60 - 16.000 Hz
USB sensitivity	-12 dBFS / Pa (Vol Max)
XLR sensitivity	-52 dBV / Pa
Standard signal	0 dB = 1 V / Pa
Maximum SPL	130 dB, 1 kHz @ 1% THD
USB compatibility	USB 1.0 / USB 1.1 / USB 2.0 / USB 3.0
ADC / DAC support	16 bit and 24 bit PCM format
Sampling Rates for Recording	44.1 kHz / 48 kHz / 96 kHz / 192 kHz
Dimensions	30 ~ 51 (Ø) mm × 183 ±2 mm
Headphone output	3.5 mm phone socket
Headphone output power	10 mW @ 16 Ω
System requirements	Win 7 / Win 8 / Win 10 / Mac OS

### Intended use

This device is intended to be used to convert acoustic signals to electric signals. Any other use or use under other operating conditions is considered to be improper and may result in personal injury or property damage. No liability will be assumed for damages resulting from improper use.

### Danger for children



Ensure that plastic bags, packaging, etc. are properly disposed of and are not in the reach of babies and young children. Choking hazard! Ensure that children do not detach any small parts from the product. They could swallow the pieces and choke! Never let children use electrical devices unattended.

### Possible staining

The plasticiser contained in the rubber feet of this product may possibly react with the coating of your parquet, linoleum, laminate or PVC floor and after some time cause permanent dark stains. In case of doubt, do not put the rubber feet directly on the floor, but use felt-pad floor protectors or a carpet.

### Disposal of the packaging material



For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose these materials with your normal household waste, but make sure that they are fed to a recovery. Please follow the notes and markings on the packaging.

### Disposal of your old device



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE) in its currently valid version. Do not dispose of your old device with your normal household waste. Dispose of this product through an approved waste disposal firm or through your local waste facility. Comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.