

EΝ

## GZ 1 USB - USB pressure zone mic

**USB** powered Mini jack headphone output **Micro USB connection** 125 cm micro-USB to USB-A cable included No driver installation required under Win 7 / 8 / 10 & MAC OS 9 / X **Caution!** Never open the microphone housing, as this may damage the microphone capsule! Never drop the mic, as this may cause severe damage! When the microphone is not in use, take it out of its clamp and put it in its case. Clean with damp cloth only. 20 -30 -40. -50.0 -60 -70.0 200 Polar pattern @ 1 kHz Connection / Supply USB / 5 V ----

Sample rate	48 kHz
Resolution	16 bit
Directivity	cardioid
Sensitivity	-54 dB (@ 1 kHz, 0 dB = 1 V / u, bar)
Signal-to-noise ratio	55 dB (@ 1 kHz)
Maximum SPL	110 dB (@ 1% THD)
Frequency response	50 – 18,000 Hz
Colour	black
Dimensions ( $L \times W \times H$ )	$90 \times 90 \times 25.7 \text{ mm}$
Weight	approx. 190 g

For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging. This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE) in its currently valid version. Do not dispose of your old device with your normal household waste. Dispose of this product through an approved waste disposal firm or through your local waste facility. Comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.