



- The device distributes an HDMI input signal to four HDMI outputs
- Resolution up to 2160p30 and 1080p60
- Supports HDMI 1.4
- HDMI-A in and outputs
- Supports 12-bit Deep Full HD, 3D and 4K x 2K video
- Supports standard audio, DSD audio and HD audio (HBR)
- Status LEDs for power supply, HDMI input and outputs
- Metal and plastic housing
- Power adapter and adapter plug included

Technical specifications

▪ Resolutions	Input	up to 2160p30 and 1080p60
	Output	up to 2160p30 and 1080p60
▪ Format	HDMI 1.4	
▪ HDCP	yes	
▪ Colour depth	12 bit	
▪ Audio formats	Standard Audio, DSD Audio and HD Audio (HBR)	
▪ Audio inputs	./.	
▪ Audio outputs	./.	
▪ Input connections	1 x HDMI type A	
▪ Output connections	4 x HDMI type A	
▪ Power supply	External power adapter, 100 - 240 V~ 50 / 60 Hz	
▪ Operating voltage	5 V / 1 A, centre positive	
▪ Degree of protection	IP20	
▪ Dimensions (W x D x H)	111 mm x 22 mm x 60 mm	
▪ Weight	0,2 kg	
▪ Ambient conditions	Temperature range	0 °C...40 °C
	Relative humidity	20 %...80 % (non-condensing)

Intended use

This device is intended to distribute a digital HDMI signal to four outputs. Any other use or use under other operating conditions is considered to be improper and may result in personal injury or property damage. No liability will be assumed for damages resulting from improper use.

Risk of injury and choking hazard for children!

Children can suffocate on packaging material and small parts. Children can injure themselves when handling the device. Never allow children to play with the packaging material and the device. Always store packaging material out of the reach of babies and small children. Always dispose of packaging material properly when it is not in use. Never allow children to use the device without supervision.

Damage to the external power supply due to high voltages!

The device is powered by an external power supply. The external power supply can be damaged if it is operated with the incorrect voltage or if high voltage peaks occur. In the worst case, excess voltages can also cause a risk of injury and fires. Make sure that the voltage specification on the external power supply matches the local power grid before plugging in the power supply. Only operate the external power supply from professionally installed mains sockets that are protected by a residual current circuit breaker (FI). As a precaution, disconnect the power supply from the power grid when storms are approaching or if the device will not be used for a longer period.



Possible staining

The plasticiser contained in the rubber feet of this product may possibly react with the coating of your surface and after some time cause permanent dark stains. In case of doubt, do not put the rubber feet directly on the surface and use a suitable underlay if necessary, i.e. felt pads or similar.



For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.



This product is subject to the European Waste Electrical and Electronic Equipment Directive (WEEE) in its currently valid version. Do not dispose of your old device with your normal household waste. Dispose of this product through an approved waste disposal firm or through your local waste facility. Comply with the rules and regulations that apply in your country. If in doubt, consult your local waste disposal facility.

